

Poruke na micro:bitu – radni listić

Zadatak 1

Poveži blok s njegovim opisom.

Pošalji znakovni niz

Postavi broj radio grupe

Pošalji broj

Kada primiš znakovni niz

Kada primiš broj

Pošalji znakovni niz i broj

```
radio set group 1
```

```
on radio received receivedNumber
```

```
radio send value "name" = 0
```

```
radio send string ""
```



```
on radio received receivedString
```



```
radio send number 0
```

Zadatak 2

U idućim programima pronađi i ispravi grešku kod micro:bit pošiljatelja ili micro:bit primatelja kako bi micro:bitovi uspješno komunicirali. Programe testiraj s micro:bitovima.

	Micro:bit pošiljatelj	Micro:bit primatelj
a)	<pre>on start radio set group 1 radio send string "Srce"</pre>	<pre>on start radio set group 11 on radio received receivedString show icon [grid icon]</pre>

	Micro:bit pošiljatelj	Micro:bit primatelj
b)	 <pre> on start radio set group 3 every 60000 ms radio send number temperature (°C) </pre>	 <pre> on start radio set group 3 on radio received receivedString show number receivedNumber </pre>

	Micro:bit pošiljatelj	Micro:bit primatelj
c)	 <pre> on start radio set group 45 on button A pressed radio send string "Melodija 1" show icon pause (ms) 100 clear screen on button B pressed radio send string "Melodija 2" show icon pause (ms) 100 clear screen </pre>	 <pre> on start radio set group 45 show icon on radio received receivedString if receivedString = "Melodia 1" then play melody at tempo 120 (bpm) until done else play melody at tempo 120 (bpm) until done </pre>